

RLC-820A

Smart 4K Ultra HD PoE Security IP Camera with Person/Vehicle Detection; IP66 Waterproof

- Person/Vehicle Detection
- 4K 8MP Ultra HD
- 100ft Night Vision



Specifications

Video & Audio	
Image Sensor	1/2,7" CMOS sensor
Video Resolution	Default: 3840X2160 (8.0 Megapixels) at 25 frames/sec
Lens	f=4.0mm fixed; F=2.0, with IR-cut filter
Video Compression	H.265/H.264
Field of View	• Horizontal: 87° • Vertical: 44°
Day & Night	IR-cut filter with auto-switching
Night Vision	30 meters (100 ft) (LED: 18pcs/14mil/850nm)
Audio	Audio recording
Power	
PoE	IEEE 802.3af, 48V Active
DC Power	DC 12.0V 1A, <12W
Interface	
Power	DC power port

System	Reset button
Ethernet	One 10M/100Mbps; RJ45
Storage	MicroSD card slot (Max. 512GB)
Audio	Built-in microphone
Software Features	
Frame Rate	• Mainstream: 2fps - 25fps (default: 25fps) • Substream: 4fps - 15fps (default: 10fps)
Code Rate	• Mainstream: 4096Kbps - 8192Kbps (default: 6144Kbps) • Substream: 64Kbps - 512Kbps (default: 256Kbps)
Browser Supported	Edge, Chrome, Firefox, Safari
OS Supported	PC: Windows, Mac OS; Smartphone: iOS, Android
Smart Alarm	Motion detection; person detection; vehicle detection; pet detection
Record Mode	Motion-triggered recording (default); scheduled recording; 24/7 recording
Protocols & Standards	HTTPS, SSL, TCP/IP, UDP, HTTP, IPv4, UPnP, RTSP, RTMP, SMTP, NTP, DHCP, DNS, DDNS, FTP, P2P
Maximal User Access	20 users (1 admin account & 19 user accounts); support up to 12 simultaneous video streams (10 substreams & 2 mainstreams)
Smart Home	Google Assistant
Working Environment	
Temperature	Operating temperature: -10°C ~ +55°C (14°F ~ 131°F)
Humidity	Operating humidity: 10% ~ 90%
Weatherproof	IP67
Size & Weight	
Dimensions	Φ105*95mm
Weight	467.5g
Warranty	
Limited Warranty	2-year limited warranty. For support, visit https://support.reolink.com/hc/en-us/

Gallery & Specs



1. Mount
2. Metal Aluminum Case
3. High Definition Lens (f=4.0mm)
4. 18 IR LEDs
5. Daylight Sensor
6. Built-In Mic



Only Manual Rotation



1. micro SD Card Slot
- Tip: Rotate the lens to find the micro SD card slot on the bottom.



1. Power
2. Reset Button
3. Network
4. Waterproof Lid

